



## SNL2-E – Serial Network Link

### SNL2-E Ethernet/RS232/RS485 Gateway

#### Description

SNL2-E – the optimal solution for connection of serial interfaces and Ethernet networks of up to 100 Mbit/s.

SNL2-E allows the connection of two serial end devices. The serial interfaces can be configured via software as RS232- or RS422/RS485 interfaces. Also, a mixed operation mode is possible.

In addition, for operating the RS485 bus, terminating resistors can be switched on via software. Operation in TTY mode can be realized by means of an external adapter.

Both interfaces support full duplex DMA mode operation. In synchronous operation mode, rates of up to 1 Mbit/s can be reached.

The protocol firmware is loadable. The serial interfaces can be run completely

independent from each other. On every serial interface a different protocol driver can be loaded and run.

The following protocols are supported:

- DK3964R/PTS5 (RK512)
- freely definable ASCII-Protocol
- LSV2 (on demand)
- MSV2
- HDLC-UNC-2
- HDLC Frame Level
- HDLC-BAC 2.8
- X.25
- SINEC-L1

Various access options are offered from the network side:

Access via TCP/IP-Socket-Interface  
Access is made directly via the socket-interface by send and receive-calls. This allows for a complete independence of the PC operating system in use. On the PC or

workstation, no driver needs to be installed, only a TCP/IP connection must be available.


DF-compatible driver interface

For Windows, as well as UNIX operating systems the DF-board compatible interface allows the replacement of an existing DF-board by an SNL2-E module without any changes in the application software. Compared to solutions based on conventional PC communication boards, SNL2-E offers completely new aspects for the connection of PC-based systems:

- Hardware/driver installation with its typical problems is bypassed
- Access to the serial interface is possible from every PC in the network
- Trouble-free integration of lower automation levels into the control and design level



SNL2-E – Serial Network Link



## Technical Data

Interfaces	Ethernet Serial	10/100 BaseT 2 x RS232/RS485 (SUB-D 15 pole) 1 x RS232 (screw terminal, configuration interface)
Baud Rates	Ethernet  Serial RS232 Serial RS485	max. 100 Mbit/s  1 Mbit/s synchronous , 38,4 Kbit/s asynchronous 1 Mbit/s synchronous , 38,4 Kbit/s asynchronous
Supported Protocols	RS232 configuration interface	19,2 Kbit/s asynchronous
	DK3964R/PTS5, freely definable ASCII-Protocol, LSV2, MSV2, HDLC-UNC-2, HDLC Frame Level, HDLC-BAC 2.8, X.25, SINEC-L1	

## Order Numbers

Order No.	Item
4000-2-S 0 0 -H-*	SNL2-E Hardware
4000-2-S 0 -3-*	Board Driver
D	LINUX driver
M	Windows NT/2000/XP driver
4000-2-S o -3-*	Protocol Driver
A	COMDRV (3964R, S5) RK512
B	UNIDRV (XON/XOFF, LAUF)
D	HDLC UNC-2
E	HDLC BAC 2.8
F	X.25
J	MSV2
K	HDLC FRAME LEVEL
L	SINEC-L1
	Additional Equipment
4000-2-4 0 1 -H	RS232 adapter line from 15 to 25 pins (0.2 m) in pairs
4000-2-4 0 3 -H	V11/TTY adapter
4000-7-0 0 4 -S	Serial cable set for SNL2-E
4000-7-0 0 5 -S	Ethernet cross-over cable
4000-7-0 0 S -H	Power supply 24V/0,65 A with power boost for up to 2 SNL2-E
4000-7-0 1 S -H	Power supply 24V/2 A with power boost for up to 5 SNL2-E

\* Please complete the order number either with E for a documentation in English or D for a documentation in German.